

ELATION® CUEPIX BLINDER WW2™					
DMX Channel Values / Functions VERSION 2 (4 DMX Channels)					
Specifications are subject to change without any prior written notice.					
<i>*Control of LEFT and RIGHT COB Modules chase direction depends on the Flip setting.</i>					
MODE / CHANNEL				VALUE	FUNCTION
1 CH	2 CH	3 CH	4 CH		
1	1	1			MASTER DIMMER
				0-255	Intensity 0 to 100%
			1		*LEFT COB MODULE DIMMER
				0-255	Intensity 0 to 100%
			2		*RIGHT COB MODULE DIMMER
				0-255	Intensity 0 to 100%
		2	3		FLASH / STROBE
				0-31	COB OFF
				32-63	COB ON
				64-95	FLASH Strobe Effect SLOW to FAST
				96-127	COB ON
				128-159	PULSE Strobe Effect SLOW to FAST
				160-191	COB ON
				192-223	RANDOM Strobe SLOW to FAST
				224-255	COB ON
	2	3	4		DIMMING CURVE MODES
				0-41	STANDARD
				42-84	STAGE
				85-127	TV
				128-170	ARCHITECTURAL
				171-213	THEATRE
214-255	Default to Unit Setting				

ELATION | CUEPIX BLINDER WW2™ | dmx traits

Elation Professional USA | 6122 S. Eastern Ave. | Los Angeles, CA. 90040

323-582-3322 | 323-832-9142 fax | www.elationlighting.com | info@elationlighting.com

Elation Professional B.V. | Junostraat 2 | 6468 EW Kerkrade, Netherlands

+31 45 546 85 66 | +31 45 546 85 96 fax | www.elationlighting.eu | info@elationlighting.eu